

USERS' MANUAL

BR-58UM

UHF MICROPHONE SYSTEM

BR-58UM

Professional Wireless Microphone system



Thank you for purchasing our wireless microphones. We take pride in providing our customers with the most advanced and highest quality karaoke products in the market. Please read this USER'S MANUAL before operation to ensure proper usage, and keep it for future reference. Enjoy!

Table of Contents

Table of Contents.....	1
Included Accessories.....	1
Receiver Front Panel/Rear Panel.....	2
Transmitters/Function Descriptions.....	3
Installation/Connection.....	4
Troubleshooting.....	5
Features & Specifications.....	6

Parts checklist

Before installing your wireless microphone system, here something you should know as below

Receiver.....	1	1/4" Cable.....	1
Handheld Micro.....	2	AA battery.....	4
DC Power Suppl.....	1	User Manual.....	1

*Be sure to keep original packaging in case of re-shipping is needed.

Matters Need Attention

- 1) Check to see whatever the local voltage accord with operating receiver voltage (Wrong selection may lead to burn out of receiver)
- 2) Do not dismantle the machine on your own. For internal repairing, please contact the local distributor or accepted service center.
- 3) When the machine will not be used for a long time, please disconnect the power plug from the receiver.
- 4) Do not recharge your batteries unless the batteries are rechargeable.

Cleaning

Please make sure the power is disconnected before cleaning or repairing the machine. The machine can be cleaned by using a soft cloth with water. Dry the machine with a dry cloth and let it air dry for 15 minutes. Please do not use volatile gasoline, diluents or other chemicals to clean the machine or the surface will be damaged.

Features and specifications

Features:

- Transmitter and receiver matching automatically via infrared.
- Transmitter with LED display.
- Noise reduction technology.
- Special for Karaoke halls, stages or home entertainments.

Specifications:

Receiver

- Frequency Range: UHF 480.00-570.00 MHz
- Dynamic Range: >90dB
- Frequency Response: 40Hz--18KHz
- Frequency Stability: <+30ppm
- Sensitivity: <-105dBm
- S/N Ratio: >95dB
- T.H.D.: <0.5%
- Image Rejection: >85dB
- Spurious Rejection: >85dB
- Max Output Level: Balance: 0-400mV; Unbalance: 0-200mV
- Power Supply: DC 12-15V

Transmitter


- Modulation Type: FM
- Transmitter Power: 30mW
- Spurious Emission: >60dB
- Battery Voltage: 3V (2pcs x 1.5V AA Batteries)
- Continuous Working: about 5 hours

Troubleshooting

If you are having operating problems, or suspect something wrong with the unit, please check the troubleshooting list below to see if the issue is a result of incorrect operation rather than equipment malfunction.


Problem	Possible cause	Solution
Receiver No sound; No lights	<ul style="list-style-type: none"> • Power button is on the OFF position • DC power adapter is not plug in • Poor connection of DC power adapter • How to switch from different channels? 	<ul style="list-style-type: none"> • Turn on the power button • Plug in the DC power adapter • Check to see if the DC power adapter is loose. • See page 3 for details.
Microphone No sound; Lights on	<ul style="list-style-type: none"> • The transmitter is out of range • Microphone switch is off or mute • Microphone volume is turned down • Batteries in the microphone are not installed properly • The antenna is not fully functional. • Receiver is not connected to an amplifier, mixer or karaoke player 	<ul style="list-style-type: none"> • Operate the machine in the effective range • Turn on the microphone switch (indicated green light) • Turn on the microphone volume of the receiver • Reinstall the batteries. Make sure the positive and negative end are install correctly • Try to change the angel of the antenna • Connect the 1/4 to 1/4 cable from the receiver to a microphone input (mixer, player, etc.). See Page 4 for detail
Distorted sound; feedback	<ul style="list-style-type: none"> • The two microphones are too close together • Batteries running low in microphone • Microphone volume is too high • Distortion from other electric wave 	<ul style="list-style-type: none"> • Separate the microphone further away • Replace the batteries • Reduce the volume of the microphone • Move the receiver away from electric equipment
Batteries	• Batteries are bad or off power	• Replace the batteries.

Receiver Front Panel




- ① Ant.
- ② Power Switch: turn on/off
- ③ Menu Bottom: SET button
- ④ Menu Bottom: Up button
- ⑤ Menu Bottom: Down button
- ⑥ LED Display: showing all information
- ⑦ IR Window
- ⑧ VOL. control

Receiver Rear Panel



- ① Ant.
- ② DC Input
- ③ Mix Out
- ④ Balance Audio Output

Transmitters




1. Antenna
2. Power Switch: Press the button for 2-3 seconds to turn on, the LED lights. Press again for 2-3 seconds to turn off.
3. Audio Input Interface.
4. LED Indicator: Light when turn on. Flashes when low power.
5. LCD Display: Display frequency in formation.
6. Adjustment Touch Set: Set button is in the middle. Touch it to enter and adjust the volume menu. Touch the left and right buttons to adjust.
7. Infrared Data Receive Window: receive data transmitted signal.
8. Battery Store.
9. Battery Cover.

- ① Microphone Grille: cartridge inside
- ② LED Display
- ③ Power Switch: turn on/off
- ④ Battery Store

Function Discriptions

- 1) Select frequency: press one time "UP" or "DOWN" button, left or right "CH" flashing, then press "UP" or "DOWN", the frequency will be changed.
- 2) Choose the channel/frequency: when "CH" is changed, press "SET" to confirm the channel/frequency you want.
- 3) IR: put the transmitter near to IR light in receiver, then press "SET", the transmitter will match to the frequency of receiver automatically.

Installation



- 1) Contact with 12-15V 1000mA DC adaptor.
- 2) Connect one end of a 1/4" TO 1/4" CABLE to the receiver's UNBALANCE AUDIO OUTPUT (MIX) and the other end to a karaoke mixer, karaoke player or karaoke power amplifier 1/4" microphone input. If you are using the BALANCE AUDIO OUTPUT, use a XLR to XLR cable or XLR to 1/4" cable.
- 3) Unscrew the microphones (handle to counter-clockwise) to check to see if there are batteries. If not, put the batteries into the microphones with the negative and positive end of the battery correspond the negative and positive end of the microphone. Screw the microphone handle back on.

Connected

- 1) The power supply is connected to the power input of the receiver. The input voltage of the power adapter must be consistent with the local power specifications.
- 2) XLR balanced output and 6.3mm unbalanced output jack on the rear panel of the receiver, based on the need to be connected.